

Quick Reference Guide For Partner ACS R5 – System Programming

System Programming – From extension 10 or 11 (Any MLS display phone) dial **Feature 00**, then press the **Left Intercom** button 2 times to enter **System Programming**. The numbers in parentheses after the program item heading are the factory default values. To end the **System Programming** session dial **Feature 00**.

System Date (010100)

Dial #101

Dial date (MMDDYY)

System Time (0000)

Dial #103

Dial time (HHMM) in 24-hour format

Number of Outside Lines

Dial #104

Dial number of lines (01-31)

Transfer Return Rings (4)

Dial #105

Dial return rings (0-9), 0=No return

Recall Timer (18=450msec)

Dial #107

Dial recall interval (01-80)

Each increment of 1 = 25msec

Rotary Dial Timeout (2)

Dial #108

1=4 sec, 2=8 sec, 3=12 sec

Outside Conference Denial (1)

Dial #109

1=Allowed, 2=Disallowed

ASA Delay (2)

Dial #110

Dial ring delay (0-9)

ASA Button (Ext. 10) (2)

Dial #111

1=Assigned to next available button w/lights,

2=Not assigned, 3=Press button to custom assign

DXD Delay (2)

Dial #112

Dial Ring Delay (0-9)

DXD Button (Ext. 10) (2)

Dial #113

1=Assigned to next available button w/lights,

2=Not assigned, 3=Press button to custom assign

Outgoing Call Restrict Button (2)

Dial #114

1=Assigned, 2=Not assigned,

3=Select button

Quick Reference Guide For Partner ACS R5 – System Programming

Wake Up Service Button (2)

Dial #115

1=Assigned, 2=Not assigned,
3=Select button

Ring On Transfer (1)

Dial #119

1=Active, 2=Not active

ASA Mode (1)

Dial #121

1=Hold, 2=Disconnect,
3=Ring a programmable button

Caller ID Type (1)

Dial #122

1=USA, 2=Singapore

Backup Programming – Auto (2)

Dial #123

1=Active, 2=Not active,
3=Backup alarm cleared

Backup Programming – Manual

Dial #124

Press **Enter** to begin backup

Restore Programming (1)

Dial #125

1=Manual MMDDYY,
2=Automatic MMDDYY
Press **Enter** to begin restore

Auto Daylight/Standard Times (1)

Dial #126

1=Active, 2 = Not active

System Mode (Key)

Dial #198

Key = 8632851
Pool = 8632852
System will restart

Dial Mode (1)

Dial #201

Dial line number (01-31)
1=Touchtone, 2=Rotary

Hold Disconnect Timer (09)

Dial #203

Dial line number (01-31)
00=None, 12=600msec (Each
increment of 01 = 50msec)

ASA Lines (2)

Dial #204

Dial line number (01-31)
1=Assigned, 2=Not assigned

DXD Lines (2)

Dial #205

Dial line number (01-31)
1=Assigned, 2=Not assigned

Quick Reference Guide For Partner ACS R5 – System Programming

Group Call Distribution (2)

Dial #206
Dial group number (1-6, 7 = VMS group)
Dial line number (01-31)
1=Assigned, 2=Not assigned, 3=VMS Cover

Line Coverage Extension

Dial #208
Dial line number (01-31)
Dial extension (10-49)

Line Assignment

Dial #301
Dial extension (10-49)
Dial line number (01-31)
1=Assigned, 2=Not assigned
3=Select button

Language (1)

Dial #303
1=English, 2=Spanish, 3=French

Abbreviated Ring (1)

Dial #305
Dial extension (10-49)
1=Active, 2=Not active

Forced Account Code Entry (2)

Dial #307
Dial extension (10-49)
1=Assigned, 2=Not assigned

Pool Line Assignment (2)

Dial #207
Dial line number (01-31)
1=No pool, 2=Main pool 880,
3=Pool 881, 4=Pool 882, 5=Pool 883

Unique Line Ringing (1)

Dial #209
Dial line number (01-31)
Dial ring pattern (1-8)

Line Access Restriction (1)

Dial #302
Dial extension (10-49)
Dial line number (01-31)
1=No restriction, 2=Out only,
3=In only, 4=No access

Automatic Extension Privacy (2)

Dial #304
Dial extension (10-49)
1=Assigned, 2=Not assigned

Transfer Return Extension(*)

Dial #306
Dial extension (10-49)
Dial extension to which a transferred
call will be returned (10-49)
* = Extension transferring call

Distinctive Ring (1)

Dial #308
Dial extension (10-49)
1=Active, 2=Not active

Quick Reference Guide For Partner ACS R5 – System Programming

Intercom Dial Tone (1)

Dial #309
1=Regular, 2=Machine

Automatic VMS Cover (2)

Dial #310
Dial extension (10-49)
1=Assigned, 2=Not assigned

External Hotline (2)

Dial #311
Dial extension (10-49)
1=Assigned, 2=Not assigned

Voice Interrupt On Busy (2)

Dial #312
Dial extension (10-49)
1=Assigned, 2=Not assigned

Line Access Mode

Dial #313
Dial extension (10-49)
1=Pool (All except 10)
2=Key

Pool Extension Assignment

Dial #314
Dial Extension (10-49)
Dial Pool Access Code (880-883)
1=Assigned, 2=Not Assigned,
3=Select Button

Pool Access Restriction (1)

Dial #315
Dial extension (10-49)
Dial Pool Number (880-883)
1=No restriction, 2=Outgoing only,
3=Incoming only, 4=No access

Call Waiting (2)

Dial #316
Dial extension (10-49)
1=Assigned, 2=Not assigned

Caller ID Log Answered Calls (2)

Dial #317
Dial extension (10-49)
1=Active, 2=Not active

Caller ID Call Log Line Association

Dial #318
Dial extension (10-49)
Dial line number (01-31)

Caller ID Log All Calls (*)

Dial #319
Dial extension (10-49)
* =No extension assigned

Call Coverage Rings (2)

Dial #320
Dial number of rings (1-9)

Quick Reference Guide For Partner ACS R5 – System Programming

VMS Cover Rings (3)

Dial #321
Dial extension (10-49)
Dial target extension (10-49)

Outgoing Call Restrictions (1)

Dial #401
Dial extension (10-49)
1=No restriction, 2=Inside only,
3=Local only

System Password

Dial #403
Dial 4 digits to set password

Disallowed List Assignment (2)

Dial #405
Dial extension (10-49)
Dial list number (1-8)
1=Assigned, 2=Not assigned

Allowed Phone Number List

Dial #407
Dial list number (1-8)
Dial list entry (01-10)
Dial phone number (12 digits max.)
Press **Enter**

Forced Account Code List

Dial #409
Dial list entry (01-99)
Dial account code (Up to 6 digits)
Press **Enter**

Copy Settings

Dial #399
Dial source extension (10-49)
Dial number of rings (1-9)

Toll Call Prefix (1)

Dial #402
1=0/1 + Area Code,
2=Area Code only

Disallowed Phone Number List

Dial #404
Dial list number (1-8)
Dial list entry (01-10)
Dial phone number (12 digits max.)
Press **Enter**

Emergency Phone Number List

Dial #406
Dial list entry (01-10)
Dial phone number (12 digits max.)
Press **Enter**

Allowed List Assignments (2)

Dial #408
Dial extension (10-49)
Dial list number (1-8)
1=Assigned, 2=Not assigned

Star Code Dial Delay (0)

Dial #410
Dial delay in seconds (0-5),
6=Not active

Quick Reference Guide For Partner ACS R5 – System Programming

Pickup Group Extensions (2)

Dial #501
Dial group number (1-4)
Dial extension (10-49)
1=Assigned, 2=Not assigned

Night Service Button (Extension 10 Only) (2)

Dial #503
1=Assigned to next available button w/lights
2=Not assigned
3=Press a button with lights to custom assign

Hunt Group Extensions (2)

Dial #505
Dial group number (1-6, 7 = VMS group)
Dial extension (10-49)
1=Assigned, 2=Not assigned

VMS Hunt Schedule (1)

Dial #507
Dial line number (01-31)
1=Always, 2=Day only, 3=Night only

Fax Extension (2)

Dial #601
Dial extension (10-49)
1=Assigned, 2=Not assigned

Hotline

Dial #603
Dial hotline extension (**NOT** 10, or the first
2 extensions of any 206 or 308)
Dial alerted extension (10-49, or 70 for page)

Calling Group Extensions (2)

Dial #502
Dial group number (1-4)
Dial extension (10-49)
1=Assigned, 2=Not assigned

Night Service Group (2)

Dial #504
Dial extension (10-49)
1=Assigned, 2=Not assigned

VMS Hunt Delay (2)

Dial #506
Dial 1 (day), or 2 (night)
Dial line number (01-31)
Dial number of rings (0-6)

Music-On-Hold (1)

Dial #602
1=Active, 2=Not active

Doorphone 1 Extension

Dial #604
Dial extension (Any except first
2 extensions of any 206 or 308)

Quick Reference Guide For Partner ACS R5 – System Programming

Doorphone 2 Extension

Dial #605
Dial extension (Any except first 2
extensions of any 206 or 308)

AA Extensions (2)

Dial #607
Dial extension (10-49)
1=Assigned, 2=Not assigned

SMDR Top Of Page

Dial #609

SMDR Talk Time (2)

Dial #611
1=Active, 2=Not active

Contact Closure Operation Type (2)

Dial #613
Dial a contact closure (1-2)
1=1 sec. On, 2=3 secs. on,
3=5 secs. on, 4=Toggle

System Reset

Dial #728
All calls disconnected,
all programming saved

System Initialization

Dial #989
Display “Restart – Defaults”
Dial 25327 (CLEAR)
System is returned to factory default

Doorphone Alert Extensions (1)

Dial #606
Dial extension (10-49)
1=No Alert, 2=Door 1 Alert,
3=Door 2 Alert, 4=Door 1&2 Alert

SMDR Record Type (1)

Dial #608
1=All calls, 2=Outgoing calls only

SMDR Output Format (1)

Dial #610
1=15 digits, 2=24 digits

Contact Closure Group (2)

Dial #612
Dial group number (1-2)
Dial extension (10-49)
1=Assigned, 2=Not assigned

Music On Hold Volume (4)

Dial #614
Dial volume (1-7)

Remote Administration Password

Dial #730
Current password displayed
Enter password (Up to 8 characters,
use 2-digit character codes on p. 10)

Quick Reference Guide For Partner ACS R5 – Centralized Programming

Centralized Programming – From extension 10 or 11 (Any MLS display phone) dial **Feature 00**, press the **Left Intercom** button 2 times, then press the **Right Intercom** button 1 time to enter **Centralized Programming**. The following station features can **only** be changed in **Centralized Programming**. To program another extension, press the **Right Intercom** button. Dial **Feature 00** to end the programming session.

Automatic Line Selection (Do this procedure first before programming other features)

Dial extension (10-49)

Dial **

Press line or pool buttons in the order of desired selection. (To select intercom dial tone, press the **Left Intercom** button first, then press line or pool buttons in the order of desired selection.)

Dial ** to end

Line Ringing

Dial extension (10-49)

Observe the green lights for each line or pool assigned to the extension.

Immediate Ring = Steady light

Delayed Ring = Slow flashing light

No Ring = Fast fluttering light

Press each line or pool button until the desired ring option is set.

Quick Reference Guide For Partner ACS R5 – Station Features

To program a feature to a station button follow one of the following procedures:

Station Programming (At the station being programmed)

Dial **Feature 00**

Press the button to be programmed

Press the **Feature** button, then dial a feature code listed below

Program another button, or dial **Feature 00** to end

Centralized Programming (At Station 10 or 11 Only)

Dial the extension (10-49) to be programmed

Press the button to be programmed

Press the **Feature** button, then dial a feature code listed below

Program another button, or dial **Feature 00** to end

Feature Codes

***Do Not Disturb = 01**

Exclusive Hold = 02

Recall (Flash) = 03

Saved Number Redial = 04

Last Number Redial = 05

Conference Drop = 06

***Privacy = 07**

Touchtone Enable = 08

Message Light On = 09

Message Light Off = 10

****Call Forwarding/Call Follow Me = 11**

****Account Code Entry = 12**

Manual Signaling = 13

Voice Mailbox Transfer = 14

***VMS Cover = 15**

***Caller ID – Name Display = 16**

***Caller ID Inspect = 17**

***Voice Interrupt On Busy = 18**

****Background Music = 19**

****Call Coverage = 20**

****Station Lock = 21**

*****Station Unlock = 22**

***Caller ID Call Logging & Dialing = 23**

***Record-A-Call = 24**

***Call Screening = 25**

****Contact Closure 1 = 41**

****Contact Closure 2 = 42**

*Requires a button with lights

**Button with lights recommended

***Do NOT program on a button

Quick Reference Guide For Partner ACS R5 – Station Features

Additional Features

Enter **Station Programming**, or **Centralized Programming**

Press the button to be programmed

Call Pickup Individual = Press **Left Intercom**, dial 6, dial extension (10-49)

Call Pickup Group = Press **Left Intercom**, dial 66, dial group (1-4)

Direct Line Pickup – Active Line = Press **Left Intercom**, dial 68

Direct Line Pickup – Idle Line = Press **Left Intercom**, dial 8

Group Calling - Ring = Press **Left Intercom**, dial 7, dial group (1-4)

Group Calling – Voice = Press **Left Intercom**, dial *7, dial group (1-4)

Group Hunting – Ring = Press **Left Intercom**, dial 77, dial hunt group (1-6)

Group Hunting – Voice = Press **Left Intercom**, dial *77, dial hunt group (1-6)

Loudspeaker Paging = Press **Left Intercom**, dial 70

Simultaneous Paging = Press **Left Intercom**, dial *70

Extension Name Display

Enter **Station Programming**, or **Centralized Programming**

Press **Left Intercom**

Dial 2-digit code for each character

(MLS display = 12 characters limit, Partner display = 20 characters limit)

| | | |
|--------|--------|------------|
| A = 21 | N = 62 | BLANK = 11 |
| B = 22 | O = 63 | 0 = 00 |
| C = 23 | P = 71 | 1 = 10 |
| D = 31 | Q = 72 | 2 = 20 |
| E = 32 | R = 73 | 3 = 30 |
| F = 33 | S = 74 | 4 = 40 |
| G = 41 | T = 81 | 5 = 50 |
| H = 42 | U = 82 | 6 = 60 |
| I = 43 | V = 83 | 7 = 70 |
| J = 51 | W = 91 | 8 = 80 |
| K = 52 | X = 92 | 9 = 90 |
| L = 53 | Y = 93 | |
| M = 61 | Z = 94 | |

Quick Reference Guide For Partner ACS R5 – Auto/Speed Dialing

Auto Dial – Inside (Station DSS/BLF)

Enter **Station Programming**, or **Centralized Programming**

Press the button to be programmed

Press the **Left Intercom** button

Dial an extension (10-49)

Note: Dial * before the extension to make this a voice call instead of a ringing call

Auto Dial – Outside

Enter **Station Programming**, or **Centralized Programming**

Press the button to be programmed

Dial outside phone number (Up to 28 digits including special dialing characters)

Personal Speed Dial

Enter **Station Programming**, or **Centralized Programming**

Press the **Feature** button

Dial a 2-Digit Code (80-99)

Dial outside phone number (Up to 28 digits including special dialing characters.)

System Speed Dial (Note: NOT Done In System Programming)

At extension 10 or 11, dial **Feature** 00

Press **Feature** followed by a 3-digit speed dial code (600-699)

Dial phone number (Up to 28 digits including special dialing characters.)

Dial **Feature** 00 to end

Special Dialing Characters

Pause (1.5 Seconds) = Press **Hold** button

Recall (Flash) = Press **Spkr** button

Stop Dialing = Press **Mic** button

Touchtone Enable = Press **Transfer** button

Restriction Override = Dial * before the phone number

J & J Communications

770-795-5462 or 888-552-6665

www.iandjcommunications.com